# NINGBO SNAPPY OPTOELECTRONICS CO.,LTD SDL200-VF





Features:

.Built-in constant voltage LED driver

.Built in push dimming

.Comply to DALI 2.0 standard(IEC 62386-101,102,207)

.Linear or log curve optional

.Dimming range 1.0-100%

.Start-up time is less than 0.5s

.Open circuit, short circuit, overload, over temperature protectior

.Efficiency greater than 92%

.For indoor lighting,office lighting

.5 years warranty

Model		SDL200-VF	
Output	VOLTAGE RANGE	12VDC	24VDC
	RATED CURRENT	4MIN-14.2MAX	2MIN-8.33MAX
	MAX OUTPUT POWER	170W	200W
	SETUP TIME	<0.5 sec.@230VAC	
	Dimming range	1.0-100%	
Input	Input mode	DALI OR PUSH DIMMING	
	VOLTAGE RANGE	220-240VAC 290-360VDC	
	INPUT POWER	<220W	
	Input current	1.2A MAX	
	Inrush current	50A MAX	
Protection	OVER CURRENT	110-160%	
	OVER VOLTAGE	18VDC MAX	36VDC MAX
	OVER TEMPERATURE	Thermal lock	
	SHORT CIRCUIT	Hiccup mode auto-recovery	
Environmer	WORKING TEMP.	-40∼45℃	
	WORKING HUMIDITY	15∼95% RH	
	STORAGE TEMP., HUMIDIT	-40∼80℃,10∼95% RH	
	TEMP. COEFFICIENT	±0.05%/℃(-10∼45℃)	
	VIBRATION	10 ~ 500Hz, 2G 10min./1cycle,30 min. each along X, Y, Z axes	
Safety&E MC	SAFETY STANDARDS	EN61347-1,EN61347-2-13	
	DALI STANDARDS	comply to DALI 2.0 standard(IEC 62386-101,102,207)	
	WITHSTAND VOLTAGE	I/P:-O/P:5.3KVDC 1mins	
	ISOLATION RESISTANCE	I/P:-O/P:50M Ohm/50	00VDC/25°C/70%RH
	HARMONIC	comply to EN61000-3-2 CLASS C(100% load)	
	EMC EMISSION	comply to EN55015,FCC PART15 ClassB	
	EMC IMMUNITY	comply to EN61000-4-2、3、4、5、	. 6、8、1 <mark>1;EN55024;EN6</mark> 1547
Others	MTBF	5 years MIL-HDBK-217F (50°C)	
	DIMENSION	429.5x32x23.5mm	
	PACKING		

## Dimming operation

#### 1 Push dimming

Function	Push time
No status change	<0.05 sec.
Push on/off	0.1-1 sec.
Dimming up or down	1.5-10 sec.
Long press in the off state,	>1sec
dimming starts from the	
minimum value	
Set 100% brightness	>11sec.

Factory setting 100%

Each time press will change the dimming direction

## 2 DALI connector

DALI protocol includes 16 groups and 64 addresses DALI protocol can be divided into 16 scene control

#### Dimming connection diagram

The DALI wiring diagram




## The PUSH dimming wiring diagram



Please select the suitable wires to ensure maximum voltage between two products should be no higher than 2V during synchronous parallel operation Dimensions





## Pin function description

Functions	Description
DA	DA signal/AC Null Wire
DA	DA signal/connect it between AC Live Wire and swit
AC/N	AC Null Wire
AC/L	AC Live Wire
Vout+	Positive polarity
Vout-	Negative polarity